

APPENDIX K

How to Reset a Password on a LexMark Optra Printer

Note: Make sure you write down the printer's ip address, subnet mask, gateway, printer name before running this process. After the NVRAM is reset, all tcp/ip information resets back to original settings. After you reset the NVRAM, you will have to enter in the tcp/ip information once again. Refer to **Appendix I, "Setting up the Lexmark Optra M410 Laser Printer to print AFMIS Reports"**

- (1) On the printer control panel, scroll to the **Network Menu**, hit select.
- (2) Choose **Network Option 1**, hit select
- (3) Scroll to **Network 1 Setup**, hit select
- (4) At Print, **hold go and left menu at the same time**. You are now at the **SE Menu**
- (5) Scroll to **NVRAM**, hit select
- (6) Scroll to **ReInit NVRAM**, hit select

Call CAO for further assistance (DSN 687-1051, 804-734-1051 commercial).